# CMa20w

## Outdoor wireless M-Bus temperature and humidity sensor

## **INTRODUCTION**

CMa20w is a wireless M-Bus communicating temperature and humidity sensor for outdoor use.

For a complete description of the product or for information in Swedish, visit the Elvaco AB website, www.elvaco.com.

## **OVERVIEW**



Service connector

LED

1.

2

3.

4.

- Push button
- Sensor pipe
- 5. Wall mounting

## **INSTALLATION**

The product can be installed and enabled in two modes. Please advise your project manager which operation mode is used in your project.

**Unencrypted mode:** Meter data is sent unencrypted and no encryption key is needed to decrypt the data.

- 1. Press and hold button (3) for 5-10 seconds until LED1 (2) flashes quickly.
- 2. Release button (3).

**Encrypted mode:** Meter data is sent in encrypted mode and the encryption key is needed to decrypt the data.

- 1. Press and hold button (3) for 10-22 seconds, until LED1 (2) flashes slowly.
- 2. Release button (3).



\* If the button is released in this mode, the CMa20w will return to inactive mode. This also applies if the button is pressed down for longer than 25 seconds.

## MOUNTING

Mount the product in a weatherproof location to avoid that direct sunlight or rain affects the sensors. The product should be mounted straight vertically and horizontally with the sensor pipe (4) downwards. Use the holes (5) when mounting on wall.

**IMPORTANT!** To assure correct sealing when assembling the lid, **first fixate the lid by pressing on all 4 corners firmly** (see picture to the right). The two screws are used to secure the lid once pressed into place, **do not use screws to put lid into place**!



## WIRELESS M-BUS

The product is delivered with the radio turned off. The radio must be manually switched on during the installation procedure. The product will not be activated until the installation procedure is started.

#### **IMPORTANT 1**

Make sure that the product is activated by pressing the button (3) during normal operation. If the product is activated in unencrypted mode, LED1 will flash quickly 5 times. If the product is activated in encrypted mode, LED1 will be illuminated for 1 second.

#### **IMPORTANT 2**

During the first 24 hours after activation it is possible to change encryption mode between encrypted and unencrypted. See section "Installation" above.

## **OPERATION**

The product will automatically, after the installation procedure, send C1 messages every 3rd minute containing sensor data, such as instantaneous temperature and humidity. The product will also send product status information, containing age indication of the battery and other relevant information.

## **SAFETY**

The warranty does not cover damage to the product caused by usage in any other way than described in this manual. Elvaco AB can not be liable for personal injury or property damage caused by usage in any other way than described in this manual.



. vvali mounting

## **TECHNICAL SPECIFICATIONS**

Mechanics			
Protection class	IP65		
Dimensions	110x100x52 mm		
Weight	140 g		
Antenna Wireless M-Bus	Internal		
Mounting	Wall mounted		
Electrical			
Power supply	Battery, 12 years		
Environmental			
Operating temperature range	-20 °C to +45 °C		
Storage temperature range	-40 to +30 °C		
Operating humidity	0 to 95 %RH no condensation		
Sensor accuracy			
Temperature 10 to 30 °C	+/- 0.2 °C		
Humidity 10 to 90 % RH	+/-2 % RH		
Wireless M-Bus	Vireless M-Bus		
M-Bus standard	EN 13757-4:2013, mode C1b		
M-Bus commands	SND_NR		
Values	Temperature, humidity, min/max/ average, momentary		
RF power	25 mW		
Frequency	868.95 MHz		
Approvals			
EMC	EN 61000-6-2, EN 61000-6-3		
Factory defaults	actory defaults		
Transmit interval	3 minutes		
Encryption mode	Optional unencrypted/encrypted (128 bit AES)		
Delivery mode	Inactive (not transmitting)		

## **ORDERING INFORMATION**

Product	Part number	Description
CMa20w	1050023	Wireless M-Bus communicating temperature and humidity sensor for outdoor use.

## **CONTACT INFORMATION**

#### Elvaco AB Technical support:

Phone: +46 300 434300 E-mail: support @elvaco.com Online: www.elvaco.com



© 2016, Elvaco AB. All rights reserved. The documentation and product are provided on an "as is" basis only and may contain deficiencies or inadequacies. Elvaco AB takes no responsibility for damages, liabilities or other losses by using this product. No part of the contents of this manual may be transmitted or reproduced in any form by any means without the written permission of Elvaco AB. Printed in Sweden. CMa20w Quick manual A4 English Document id: 1090092 Version: 6.0