



SensMax Loyalty Button L3 TS Real-time



Application	Airport, Smart building, Shopping mall, Retail store, Bank office, Post office, Washroom
Operation principle	Pressing one of three feedback buttons with smiley faces
Connectivity range	SensMax Loyalty Button L3 LR TS 150 m SensMax Loyalty Button L3 SLR TS 800 m
Radio module frequency	SensMax Loyalty Button L3 LR 868 MHz SensMax Loyalty Button L3 SLR 868 MHz
Internal memory	1000 records
Enclosure	White ABS Plastic
Power supply	AA batteries
Battery lifetime	Up to 2 years
Dimensions	67×67×25 mm
Spam filter	Intelligent digital filter for spam pressings filtration
Fixture	Double-sided adhesive tape or a plastic stand

SensMax Loyalty Button L3 TS designed for customer surveys at any business-related locations. This sensor works in real-time mode.

Customers can choose three emotion icons in their answers — happy, sad, and disappointed. The wireless customer survey button mounted on a plastic stand with a printed question.

The device delivers customer replies to a server in real-time using LAN/Internet or WiFi Internet gateway.

You can see statistical data in real-time or per 5-minutes time spans in analytical reports.

Wireless customer survey button works from AA batteries for up to 2 years. It has a powerful radio module with an extended communication range and can connect the data gateway in a range of up to 800 m.

Features:

- Wireless sensor
- Battery life up to 2 years
- Spam pressings filter
- Extended connectivity range

Data delivery to the server using:

- Real-time data gateway SensMax SMX TS